

Complete and Customizable Communications Solutions

ADECIA







"SOUND" ACCELERATES BUSINESS.

With new and ever-changing communication requirements, one thing remains the same: the need for high-quality, worry-free audio for collaboration. ADECIA helps organizations overcome challenges with implementation, configuration and room acoustics by providing all components required for a successful installation - designed to work seamlessly together to reduce set up time, costs and complexities.







Tabletop Array Microphone



Wireless Microphone System Remote Conference Processor



Complete Coverage from Sound Input to Output

ADECIA helps organizations overcome challenges with implementation, configuration and room acoustics by providing all components required for a successful installation - designed to work seamlessly together to reduce set up time, costs and complexities.

Reduce Time, Spend and Complexities

Audio/control signals can be transmitted with one network cable using the audio network standard, "Dante", solving troublesome wiring and installation problems.

Natural and Comfortable Conversation Experiences

Each microphone is equipped with various processing functions and when combined with Yamaha's original voice processing technology "HVAD" (Human Voice Activity Detection), it provides a smooth and stress-free remote conferencing experience. HVAD is Yamaha's technology to distinguish human voice from background noises. HVAD captures human voices and suppresses background noises, delivering a clear signal to the far end no matter where you meet.

Best Audio in Shortest Time

ADECIA automatically detects all components and configures them to be optimized for the room environment, taking into consideration location of speakers and microphones, reverberation characteristics of the room, and echo behavior. Setting up a room can be as easy as following the configurator through four steps of configuration

Customization Options to Fit Your Use Case

By offering a wide range of variations such as ceiling array microphones, tabletop array microphones, and wireless microphone systems, ADECIA meets the demands of different audio solutions for each conference, meeting or learning space and provides operations suitable for various environments.

Integration into All Audio **Environments**

Equipped with various interfaces such as USB, Bluetooth®, SIP, and analog audio input/output terminals, the system allows the flexibility to use both web conference systems and telephone line conferences. Supporting Windows, macOS, iOS and Android, as well as compliance with market leading UC applications, ADECIA gives you the flexibility to customize the solution to your specific needs.





RM-TT System Example





System Examples

RM-CG System Example

Sound Processing for High Quality Remote Conferencing Experience

Multi-beam Tracking (RM-CG)

Multi-beam Tracking is a signal processing technology that can track multiple speaking participants by combining the use of beamforming technology to form directivity with multiple microphone elements to pick up sound. With multiple beams, each beam tracks different speakers' voices when multiple speakers are present.



Auto Voice Tracking (RM-TT)

The RM-TT is equipped with Auto Voice Tracking (automatic speaker tracking function) in each microphone, allowing for flexible room layout and participant positioning. RM-CR automatically selects the closest microphone to the speaker to pick up sound, enabling a highly clear voice to the far end.

High-speed Echo Canceller (RM-W)

Moving microphone itself or moving things near it usually causes echoes in typical microphone system, resulting in interruptions and stress. As the RM-W is equipped with an excellent high-speed echo canceller that can instantly remove the echoes, you can experience a stress-free focused conversion.





Unique Yamaha Processing Technologies

Yamaha's unique HVAD technology distinguishes the human voice vs. noise to block unneeded sound from being sent to the far-end.

ADAPTIVE ECHO CANCELLER

While other echo canceller's measure the room and set levels once, Yamaha's adaptive echo cancellation is constantly scanning the environment for changes to deliver an uninterrupted, echo-free audio stream.

NOISE REDUCTION

When constant noise like a projector fan or air conditioner system enters the communication space, Yamaha's Noise Reduction technology removes these components to clearly convey the presenter's audio to the far-end.

AUTO GAIN Control

This sound technology automatically adjusts voice levels to deliver a consistent, optimal volume level to the far-end, no matter if some voices are louder vs. weaker or closer vs. further away from the microphone. This automatic feature enables everyone to hear or be heard at an ideal level.

DEREVERBERATION

Reverberation from an acousticaly-poor environment can make it difficult to distinguish a clear voice signal. Dereverberation suppresses these reverb components to deliver a highly-intelligible output.

Various Mounting Methods to Best Fit Your Usage

Setup Wizard

Ceiling Array Microphone RM-CG Installation

Ceiling Mount









Tabletop Array Microphone RM-TT Mount



Wireless Access Point RM-WAP-16/8 Installation



Remote Conference Processor RM-CR Installation

Rack Mount







Quick Setup (RM-CR)

Follow the setup wizard on your web browser and with just a few clicks it will automatically adjust the audio according to your system's audio routing and room environment.



Customize "Tracking Area" for More Accurate Audio Pick-up (RM-CG)

Users can now pre-set RM-CG's beam-tracking zones using a color-coded system in the Web UI.

- Green represents the overall pick-up coverage of the microphone.
- Blue delineates "focus areas" for more localized sound pick-up (up to 2 areas).
- Red creates an "exclusion area", cancelling audio pick-up where specified (up to 2 areas).

Monitoring (RM-WAP-16/8)

You can monitor radio wave conditions with the Web UI.







Flexible Application Support

Ceiling Solution

With a simple and sophisticated design, the unit blends into high-end spaces and enables a clean and clear table.







Wireless Solution

Flexibility to choose between gooseneck and boundary microphones to adapt to your use-case, creating the most comfortable conferencing space without worrying about wiring or configuration changes should the layout change.



Tabletop Solution

Scale and expand your coverage with the ability to increase the number of microphones used to fit your participant count. Up to 14 (*) microphone pods (4 mics per pod) simply connect to the PoE switch. * Without VXL1-16P, up to 16.

















Customization

The new Yamaha ADECIA microphone components can also be integrated with other Yamaha or third party components for required solutions with the open API.

* ProVisionaire or RM Device Finder may be required, please refer to the reference guide for details.

ProVisionaire: customizable control panel software for Yamaha PA systems

• RM Device Finder: application software for searching RM components in the network

Customization Options

The open interfaces and standards based integration options of the ADECIA components allow easy integration in other customized solutions. Some examples of that are:

• Expand the number of microphones beyond the number supported within the ADECIA solution · Expand solutions to peripheral devices not part of the ADECIA family, e.g. amplifiers or speakers

RM-TT System Example

Yamaha Customized Configuration Example

· Tabletop Array Microphone RM-TT Simple L2 Network Switch with PoE SWR2100P-10G • Simple L2 Network Switch with PoE SWR2311P-10G





RM-W System Example

Yamaha Customized Configuration Example

· Wireless Microphone System RM-W Series · Intelligent L2 Network Switch with PoE SWR2311P-10G · Signal Processor MTX/MRX Series · Power Amplifier PX3

· Speaker System VXL1W-24 · Customizable Control Panel ProVisionaire · USB Audio Interface



RM-CG System Example

Yamaha Customized Configuration Example

· Ceiling Array Microphone RM-CG
Intelligent L2 Network Switch with PoE SWR2311P-10G
Signal Processor MTX/MRX Series
Power Amplifier XMV4140-D

· Ceiling Speaker VXC4W · Speaker System VXS5W · Customizable Control Panel ProVisionaire

· USB Audio Interface



· Speaker System VXL1W-16

- · Customizable Control Panel ProVisionaire
- · USB Audio Interface

Ceiling Array Microphone RM-CG



Ceiling Array Microphone **RM-CG**

A ceiling array microphone equipped with unique audio signal processing technology that enables high-quality communication

- "Multi-beam Tracking" that scans for human voice and tracks simultaneous speech allowing for lively conversations
- Customize "Tracking Area" for more accurate audio pick-up
- Utilizes innovative Yamaha technologies like Adaptive Echo Canceller, Auto Gain Control, Noise Reduction, and Dereverberation
- Automatic detection and configuration with Remote Conference Processor RM-CR
- · Standard network audio support for "Dante"
- · Utilizes one PoE+ network cable connection avoiding troublesome wiring and enabling audio control via Dante
- · Supports 3 types of mounting methods for use with a variety of ceiling conditions



Frequency Response



External View





Unit: mm

Tabletop Array Microphone RM-TT



Frequency Response



Tabletop array microphones provide a comfortable sound environment with no configuration needed

- Auto Voice Tracking allows for flexible room layout and participant positioning
- · 6 types of microphone directivity to choose from, depending on your environment and audio needs
- · Achieves comfortable sound quality using the integrated Adaptive Echo Canceller, Auto Gain Control, Noise Reduction, and Dereverberation
- When using Auto Voice Tracking, RM-CR automatically selects the microphone element that provides the best audio signal of the voice
- · Standard network audio support for "Dante"

Tabletop Array Microphone

RM-T1

- · Utilizes one PoE+ network cable connection avoiding wiring problems and enabling audio control via Dante
- The included accessory allows for fixed installations of the microphones on tables









Cardioid





External View













Wireless Microphone System RM-W Series



Wireless Microphone System

Flexible wireless microphones system customized to your use case

 \cdot Wireless system using 1.9GHz, composed of access point, microphone, and charging station

- The access point supports 16/8 channels
- Available microphone formfactors: 6" (15 cm) gooseneck, 12" (30 cm) gooseneck, omnidirectional boundary, and cardioid directional boundary
- Approximately 20 hours of continuous microphone operation time using the included Li-ion battery
- Standard network audio support for "Dante"
- Utilizes one PoE+ network cable connection avoiding wiring problems and enabling audio control via Dante
- The Web UI Setup Wizard allows for effortless configuration, microphone pairing, audio routing, and other system management



Frequency Response





Directional Characteristics











RM-WGS



Wireless Microphone System RM-W Series



• Wireless microphones using 1.9GHz band

· Available microphone formfactors: 6" (15 cm) gooseneck, 12" (30 cm) gooseneck, omnidirectional boundary, and cardioid directional boundary

· Approximately 20 hours of continuous microphone operation time using the included Li-ion battery















RM-WGS



Unit: mm









- Charge time 5 hours to full charge





16/8 Channel Wireless Access Point RM-WAP-16/RM-WAP-8

- Access point of 1.9GHz band wireless microphone system
 - Supports 16/8 channels
 - Dante audio/control reception and PoE power are provided through a single network cable

Unit: mm

Microphone Charging Station **RM-WCH-8**

- Microphone charger for the wireless microphones in the RM series
- Up to 8 microphones can be charged at a time



Unit: mm

Remote Conference Processor RM-CR



Remote Conference Processor **RM-CR**

Signal processor at the heart of the ADECIA

- Up to 16 input/output devices can be connected to the processor via PoE switch, and up to 12 microphones
- (RM-CG, RM-TT or RM-WAP-16/8) can be connected when 4 of VXL1-16P speakers are connected
- Automatically recognizes connected devices on the same network for audio routing
- Equipped with the Auto Tuning functions that automatically measure and provide the optimum sound settings for the environment
- Includes the Auto Mixer functions that automatically optimizes the mixing balance of audio input via Dante
- · Supporting various input/output connections such as USB, VoIP, analog audio, and Bluetooth
- Standard network audio support for "Dante"; all compatible devices can be connected with network cables



Connections



*

MIC IN

AUX Input/Output (RCA)



External View















Unit: mm

Specifications

RM-CG Specifications

	Dimensions		560 (W) x 90 (H) x 560 (D) mm (including protrusion/microphone panel: 22mm)	
	Weight		5.6kg	
	Power Requirements		PoE (IEEE 802.3af)	
	Maximum Power	r Consumption	7.2W	
	Connector		RJ-45	
	In Operation	Temperature	0°C - 40°C	
		Humidity	30% - 90% (no condensation)	
	Storage	Temperature	-20°C - 60°C	
Ge		Humidity	20% - 90% (no condensation)	
General	Indicators		Front indicator (Mute/Unmute & Status), Network port indicator	
	Mount		Ceiling mount, Wire mount, VESA mount	
	Maximum Device RM-CR	e Number with	14 (without VXL1-16P, up to 16)	
	Accessories (* Including a spare respectively)		Construction description, (Guarantee), Grille x 1, Screws for grille (M3 x 8mm) x 5*, Screw cover x 4, Cutting template x 1, C ring x 1, Screws for C ring x 2, Hanger angle x 1, Screws for hanger angle (M4 x 20mm) x 5*, Terminal cover x 1, Safety wire x 1, Binding band x 1, Clamp plate x 2	
	Dust Protection		IP5X for dust protection (with terminal cover)	
	Plenum Rating		UL2043 (with terminal cover)	
Net	Ethernet		Dante, Remote Control, Web UI, PoE	
Network	Cable Requirements		CAT5e or higher (STP)	
	Audio I/O	Dante	1in/2out	
	Sampling Rate		48kHz	
	Bit Depth		24bit	
	Latency		58ms (including signal processing)	
	Frequency Resp	onse	160Hz – 16kHz (-10dB)	
Aı	Maximum Input (OdBFS)	Level of SPL	117.8dB SPL	
Idio	Self Noise		-0.8dBA SPL	
	SN Ratio (Ref. 94dB SPL a	at 1kHz)	94.8dBA	
	Sensitivity		-23.8dBFS/Pa	
	Dynamic Range		118.6dBA	
	Signal Processing		Multi-beam Tracking, Adaptive Echo Canceller, Noise Reduction, Dereverberation, Auto Mixer, Auto Gain Control, Parametric EQ, Output Gain	

RM-TT Specifications

Dimensions		140 (W) × 41.5 (H) × 140 (D) mm		
Weight		310g		
Power Requirements		PoE (IEEE 802.3af)		
Maximum Power Consumption		4.5W		
Connector		RJ-45		
In Operation	Temperature	0°C - 40°C		
	Humidity	30% - 90% (no condensation)		
Storage	Temperature	-20°C - 60°C		
	Humidity	20% - 90% (no condensation)		
Indicators		Mute indicator (Mute/Unmute), Status indicator, Network port indicator		
Maximum Devic RM-CR	e Number with	14 (without VXL1-16P, up to 16)		
Accessories		Installation manual, Tabletop mounting adapter, Screw for mounting x 3, Spacer x 3		
Ethernet		Dante, Remote Control, Web UI, PoE		
Cable Requirements		CAT5e or higher (STP)		
Audio I/O	Dante	1in/2out		
Sampling Rate		48kHz		
Bit Depth		24bit		
Latency		57ms (including signal processing)		
Frequency Response		160Hz - 16kHz (-10dB)		
Maximum Input Level of SPL (0dBFS)		106.8dB SPL		
Self Noise		6.3dBA SPL		
SN Ratio (Ref. 94dB SPL a	at 1kHz)	87.7dBA		
Sensitivity		-12.8dBFS/Pa		
Dynamic Range		100.5dBA		
Signal Processing		Auto Voice Tracking, Selectable Polar Pattern (Cardi- oid, Hyper-cardioid, Super-cardioid, Omnidirectional, Bidirectional, Toroid), Adaptive Echo Canceller, Noise Reduction, Dereverberation, Auto Mixer, Auto Gain Control, Parametric EQ, Output Gain		

RM-WDR/RM-WOM Specifications

			RM-WDR	RM-WOM	
	Dimensions		89.0 (W) x 26.0 (H) x 89.0 (
	Dimensions		(including rubber foot)		
	Weight		130g (including battery)	126g (including battery)	
	Power Requirements		Rechargable Li-ion Battery	y 3.6V 2350mA/h	
	Maximum Power Consumption		5.0V 0.7A		
	Connector		USB Type-C (for battery cł Charger I/F (4pin) x 1	narging) x 1,	
	Battery	Talk time	Approximately 20 hours (power on)		
		Standby Time	7 days		
		Charge Time	Full charging: 5 hours, 809	% charging: 3 hours	
Genera	In Operation	Temperature	0 °C - 40 °C		
ıeral		Humidity	20% - 85% (no condensati	on)	
	In Charging	Temperature	5 °C - 40 °C		
		Humidity	20% - 85% (no condensati	on)	
	Storage	Temperature	-20 °C - 60 °C		
		Humidity	10% - 90% (no condensation)		
	Indicators		Microphone indicator (3 colors) x 1, Battery indicator (3 colors) x 1		
	Buttons		Microphone button x 1, Battery button x 1, PAIR button x 1		
	Accessories		Battery (RM-WBT) x 1, Owr	ner's manual x 1	
	Options		Replacement Battery RM-WBT		
	Audio I/O Dante		1in/2out		
	Sampling Rate		48kHz		
	Bit Depth		24bit		
	Latency		30ms (no signal processing in High Quality mode)		
	Frequency Res	ponse	160Hz - 16kHz		
	Maximum Inpu (OdBFS)	t Level of SPL	109.4dB SPL	108.0dB SPL	
Aud	Self Noise		33.3dBA SPL	25.8dBA SPL	
io	SN Ratio (Ref. 94dB SPL	at 1kHz)	60.7dBA	68.2dBA	
	Sensitivity		-15.4dBFS/Pa	-14.0dBFS/Pa	
	Dynamic Range	9	76.1dBA	82.2dBA	
	Signal Processing		Adaptive Echo Canceller, Noise Reduction, Dereverberation, Auto Gain Control, Parametric EQ, Output Gain		
	Directivity		Unidirectional (Sensitibity: 120°)	Omnidirectional (Sensitivity: 360°)	

RM-WGL/RM-WGS Specifications

			RM-WGL	RM-WGS	
	Dimensions		89.0 (W) x 308.0 (H) x	89.0 (W) x 171.0 (H)	
	(including rubber foot) Weight		89.0 (D) mm 152g (including battery)	x 89.0 (D) mm 140g (including battery)	
			Rechargable Li-ion Battery		
	Power Requirements			7 3.0V 2330IIIA/II	
		er Consumption	5.0V 0.7A		
	Connector		USB Type-C (for battery ch Charger I/F (4pin) x 1	narging) x 1,	
	Battery	Talk time	Approximately 20 hours (p	ower on)	
		Standby Time	7 days		
		Charge Time	Full charging: 5 hours, 809	% charging: 3 hours	
G	In Operation	Temperature	0 °C - 40 °C		
Genera		Humidity	20% - 85% (no condensati	on)	
Ĕ	In Charging	Temperature	5 °C - 40 °C		
		Humidity	20% - 85% (no condensation)		
	Storage	Temperature	-20 °C - 60 °C		
		Humidity	10% - 90% (no condensatio	on)	
	Indicators		Microphone indicator (3 colors) x 1, Ring indicator (3 colors) x 1, Battery indicator (3 colors) x 1		
	Buttons		Microphone button x 1, Battery button x 1, PAIR button x 1		
	Accessories		Battery (RM-WBT) x 1, Owner's manual x 1		
	Options		Replacement Battery RM-WBT		
	Audio I/O Dante		1in/2out		
	Sampling Rate	I	48kHz		
	Bit Depth		24bit		
	Latency		30ms (no signal processing in High Quality mode)		
	Frequency Res	ponse	160Hz - 16kHz		
	Maximum Inpu (OdBFS)	t Level of SPL	114.0dB SPL		
Audi	Self Noise		36.4dBA SPL		
•	SN Ratio (Ref. 94dB SPL	at 1kHz)	57.6dBA		
	Sensitivity		-20.0dBFS/Pa		
	Dynamic Range	e	77.6dBA		
	Signal Processing		Adaptive Echo Canceller, Noise Reduction, Dereverberation, Auto Gain Control, Parametric EQ, Output Gain		
	Directivity		Unidirectional (Sensitivity:	90°)	

RM-WAP-16/RM-WAP-8 Specifications

			RM-WAP-16	RM-WAP-8	
	Dimensions		171.0 (W) x 43.0 (H) x 172.5 (D) mm		
	Weight		812g (including mounting bracket)	650g (including mounting bracket)	
	Power Requirem	ents	PoE Class 3 (IEEE 802.3af)	
	Maximum Powe	r Consumption	48.0V 0.2A		
	Connector		RJ-45		
	In Operation	Temperature	0° C - 40° C		
G		Humidity	20% - 85% (no condensati	on)	
Genera	Storage	Temperature	-20° C - 60° C		
<u>a</u> _		Humidity	10% - 90% (no condensation)		
	Indicators		Power indicator (3 colors) x 1, Status indicator (3 colors) x 1		
	Buttons		Reset button x 1		
	Mount		Wall mount, Ceiling mount (with blacket), Flat placing		
	Maximum Device Number with RM-CR		1	2	
	Accessories		Owner's manual x 1, Mounting bracket x 1		
Net	Ethernet		Dante, Remote Control, Web UI, PoE		
Network	Cable Requirem	ents	CAT5e or higher (STP)		
	Audio I/O	Dante	1in/16out	1in/8out	
Audio	Signal Processing		Adaptive Echo Canceller, Noise Reduction, Derever- beration, Auto Gain Control, Parametric EQ, Output Gain Adjustment		

RM-WCH-8 Specifications

	Dimensions		304.0 (w) x 41.5 (H) x 188.0 (D) mm (including rubber foot)
	Weight		800g
	Power Requirements		DC IN (16V, 2.4A)
	Maximum Powe	er Consumption	16.0V 2.0A
	Connector		DC IN 16V
General	In Operation	Temperature	0° C - 40° C
		Humidity	20% - 85% (no condensation)
	In Charging	Temperature	5° C - 40° C
		Humidity	20% - 85% (no condensation)
	Storage	Temperature	-20° C - 60 ° C
		Humidity	10% - 90% (no condensation)
	Indicators		ACTIVATE indicator (3 colors) x 1
	Buttons		ACTIVATE button x 1, PAIR button x 1
	Accessories		Owner's manual x 1, AC adapter x 1, Power cable x 1 (for US)/3 (for Europe)

RM-CR Specifications

	Dimensions		215 (W) x 44 (H) x 260 (D) mm
	Weight		1.6kg
	Power Req	uirements	PoE+ (IEEE 802.3at, LLDP)
	Maximum I	Power Consumption	15.0W
	In	Temperature	0°C - 40°C
	Operation	Humidity	30% - 90% (no condensation)
Genera	Storage	Temperature	-20°C - 60°C
a		Humidity	20% - 90% (no condensation)
	Indicators		Power indicator, Status indicator, Bluetooth indicator, Network port indicator x 3
	Accessories		Installation manual, USB cable (A-B) 5m (16.4ft), USB cable (A-microB) 1m (3.3ft), Rubber foot x 4, Access panel
	Options		Rack Mount Kit RM-MTL, Table Mount Kit RM-MRK
	Ether1		Dante, Remote Control, Web UI, PoE+
Net	Ether2/Ether3		Corporate Network, Remote Control, SIP, Web UI
Networl	USB Netwo	ork (Front)	USB2.0, Network Class, Web UI, Fixed IP
×	Cable Requirements		Ethernet1/2/3: CAT5e or higher (STP) USB Network: USB Cable (A-microB)
	Audio I/O	Dante	16in/16out
A		USB	USB2.0, Audio Class 1.0, Input: 2ch, Output: 2ch @48kHz
Audio		Microphone Input	XLR Balanced, Input: 2ch
		AUX	RCA Unbalanced (Line Level), Input: 2ch, Output: 2ch
		Speaker Out	RCA Unbalanced (Line Level), Output: 2ch

RM-WBT Specifications

	Dimensions		34.95 (W) x 11.15 (H) x 52.5 (D) mm
	Weight		42g
	Voltage		3.6V
	Nominal Capacity		2,350mA/h
	Maximum Charge Current		1.59V
Ger	Maximum Charge Voltage		4.20V
General	Maximum Discharge Current		2.30A
	In Operation	Temperature	0° C - 40° C
		Humidity	20% - 85% (no condensation)
	Storage	Temperature	-20° C - 60° C
	Humidity		10% - 90% (no condensation)
	Accessories	·	Safety brochure x 1

RM-W Series Common Specifications

	Radio Method	1.9GHz DECT standard
Wi:	Radio Frequency Range	[USA and Canada] 1920.0MHz - 1930.0MHz [EU, Australia, New Zealand, Norway and UK] 1880.0MHz - 1900.0MHz
	Maximum RF Power Level	[USA and Canada] 23.5dBm [EU, Australia, New Zealand, Norway, Sweden, Finland, Denmark and UK] 26.5dBm
	Maximum Coverage Distance	50m (depends on the usage environment)
	Encryption	AES (256-bit)

RM-CR Analog Input Characteristics

	Input Terminal	Input Level		
	input reminai	Nominal	Max. before Clip	
	MIC IN 1/2	-46dBu	-26dBu	
	AUX IN L/R	-14dBV	+6dBV	

RM-CR Analog Output Characteristics

Output Terminal	Output Terminal Source Impedance	For Use with Nominal	Output Level		Occurrenter
Output terminal			Nominal	Max. before Clip	Connector
AUX OUT L/R	1k Ω	10k Ω	-14dBV	+6dBV	RCA Pin
SP OUT L/R	1k Ω	10k Ω	-14dBV	+6dBV	RCA Pin

Audio	Audio I/O	Bluetooth	Version 4.2 Supported Profiles: HFP (1.6), A2DP, AVRCP Supported Code:: CVSD, SBC, mSBC Wireless Output: Class2 Maximum Communication Distance: 10m (32.8ft) (no obstacles) Radio Frequency (Operational Frequency): 2,402MHz - 2,480MHz Maximum Output Power (EIRP): 4.0dBm (2.5mW)
		SIP	Call Handling: Dial, Answer, Hold, Resume, Forwarding, Do not disturb, Redial, Call timer, Call ID, Voice mail notifications (switch configured) Call Bridging: Supports bridging SIP, USB, BT and AUX calls. Join, Split, Hold, Resume, 5+1 lines: up to 2 SIP calls, 1 USB call, 1 Bluetooth call, 1 AUX, Plus the user Codecs: G.711, G.722HD, G.729ab, G.726 DTMF Support: RTP event, SIP in-band, SIP info package Security: SRTP support (RFC 1889), IETF SIP support (RFC 3261 and companion RFCs)
	Sampling Rate		48kHz
	Bit Depth		24bit
	Latency		8ms (Dante In to USB Out, includes signal processing)
	Frequency Response		20Hz - 20kHz

Connector

XLR-3-31 (Balanced) RCA Pin

Accessories/Options



Replacement Battery **RM-WBT**

Replacement battery for RM-WDR, RM-WOM, RM-WGL, and RM-WGS.





An intelligent L2 switch that has the optimal functions for Dante and can supply PoE+ to up to 8 connected devices. Maximum 30W can be supplied from each PoE-compliant port (240W in total).





Mount kit for mounting the Remote Conference Processor RM-CR in a 19-inch rack (EIA standard).





A simple L2 switch that has the optimal functions for Dante and can supply PoE and PoE+ to connected devices. SWR2100P-10G has 9 ports available for PoE power supply and can supply maximum 30W per port (70W in total).



Table Mount Kit **RM-MTL**

Mount kit for mounting the Remote Conference Processor RM-CR under the table.



A Dante powered speaker by PoE power supply.



CaseStudies

KOKUYO Co., Ltd.

KOKUYO's Furniture Business Division provides a wide range of office furniture such as desks, chairs, and storage, as well as furniture for education, medical care, and public facilities, in addition to solution-oriented services such as office relocation. Although many Japanese companies have been hastily introducing measures to address the recent COVID-19 pandemic, KOKUYO is seeking to soon introduce new ways of working and office styles that are mindful of protecting against infectious diseases. Yamaha's ADECIA one-stop sound solution for remote conferencing has been introduced in the conference rooms and multipurpose spaces of KOKUYO's Shinagawa Live Office, which reopened in February 2021 after renovations.



With the COVID-19 Pandemic, Clients Seek to Achieve the Right Balance of Employee Safety and Security with Communication

Before the COVID pandemic, work style reform (notions such as optimizing work-life balance) was a major theme, but now it's more about employee safety and security, and coordinating between remote work and office work. In such a situation, KOKUYO decided to rapidly implement some plans to ensure safety and security while striving for innovation through promoting collaboration, such as AIRTRIEVE airborne droplet suction table for meeting rooms, which were installed in several meeting rooms, including this board meeting room.





The Shinagawa Live Office reopened in February 2021 after renovations



Board meeting room equipped with the ADECIA and AIRTRIEVE system

The ADECIA Ceiling Microphone Creates Spaces that Allow You to Concentrate on Conversation

In the case of meeting rooms used only for communication among employees, it's not too much of a concern if online conferencing microphones and cables are placed randomly onto tables, but this approach is simply not suitable for really special places of communication. One main reason for introducing ADECIA, which features panel-shaped microphones installed on the ceiling, was that it keeps the tabletop as clear and clean as possible.

Most conference tables are designed to be installed such that cabling is as inconspicuous as possible by taking out cables from a cabling space installed in the central section of the tabletop - however, when using the AIR-TRIEVE system, the air intake port occupies that position, so cables need to be run from the seating area instead, which creates hindrances for attendees and does not look attractive. Thanks to ADECIA, they were able to achieve the ultimate clean look without microphones or connection cables being visible in any way.

Since the purpose of a meeting is to watch facial expressions and read the spaces between overt remarks in order to achieve deeper communication, an environment such as this meeting room, where the table is free of clutter and you don't have to stay constantly aware of the position and distance of the microphone, is simply ideal. The design of the ceiling microphone is also highly evaluated. Not only is it installed out of sight on the ceiling -- it also blends into the ceiling without calling attention to itself.



Ceiling Array Microphone RM-CGW installed on the boardroom ceiling



The AIRTRIEVE system can reduce airborne viruses in meeting rooms by about 99% in 5 minutes

Introducing ADECIA Has Greatly Improved the Voice Quality and Practical Usability of **Remote Conferences**

The boundary microphones used previously had some problems in picking up sounds, and it was difficult to hear people with soft voices or who were distant from the microphone. They constantly had to physically hand the microphone around among speakers, turn to face the microphone, stay aware of the position of the microphone, and so on. Every time a board meeting was held, they really wanted to avoid this sort of situation. This was one of the reasons they decided to introduce ADECIA.

With ADECIA, the microphones installed in the ceiling instantly and automatically detect the direction of the sound source and pick up the sound, so meeting attendees can concentrate on the conversation without being aware of the microphone at all. Thanks to an auto gain control that distinguishes the human voice and adjusts the volume precisely, everyone present is able to hear clearly, regardless of seating position or speaking volume.

They also highly evaluated the noise reduction function. The AIRTRIEVE system, which is equipped with a powerful air purification unit, inevitably generates some intake and exhaust noise. The high-performance noise reduction function of ADECIA is effective in reducing this sort of low-freguency noise to a much less noticeable level, while clearly conveying conversational voices.

They also introduced ADECIA in a multipurpose space that contains no meeting table. Small-scale seminars and training will be held here, and with ADECIA, there is no need to adjust the arrangement or layout of microphones according to the number of users, and to worry about anyone tripping over cables when arranging the room layout. Thanks to the microphones that actively track multiple sound sources, sound can be picked up clearly no matter where the speaker is seated, which is a major advantage in a space like this.

Layout of the ADECIA System Arranged by KOKUYO



Introduced Products

- Ceiling Array Microphone RM-CGW
- Ceiling Array Microphone RM-CGB
- Remote Conference Processor RM-CR
- Dante PoE Powered Speaker System VXL1B-16P
- Intelligent L2 Network Switch with PoE SWR2311P-10G



Wide view of Meeting Room 5 (equipped with the ADECIA and AIRTRIEVE systems)



Wide view of Meeting Room 3



CONFERENCE ROOM 3



CONFERENCE ROOM 5





YAMAHA CORPORATION

© 2023 Yamaha Corporation. All rights reserved. Product features and specifications are subject to change without notice by Yamaha. All other product and company names and logos that appear in this leaflet are trademarks or registered trademarks of their respective owners. BR-ADECIA-SOLUTION-202309-EN-YUCYME